FIGURE 6: Operating mode Test for Cross Talk/ Feedthrough via channel disables

Test 6: Load CR1 for all channels pulsed, and steepest leagake sllope



Address Register contents =

R/W	R1	R0	A6	A5	A4	A3	A2	A1	A0
0	0	1	1	0	0	0	0	0	0

CR1 Register contents =

T1	T2	T3	T4	T5	T6	T7	T8	T9	T10	T11	T12	T13	T14	T15	T16	DS3	DS2	DS1
1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	0	0	0

Test 6(contd): Test amplitude = 90fC (test amplitude DAC=90); threshold = 2fC (threshold DAC = 48), att=1(00) in CR2 register



Address Register contents =

R/W	R1	R0	A6	A5	A4	A3	A2	A1	A0
0	1	0	1	0	0	0	0	0	0

CR2 Register contents =

At2	At1	Vt6	Vt5	Vt4	Vt3	Vt2	Vt1	Ta7	Ta6	Ta5	Ta4	Ta3	Ta2	Ta1
0	0	1	1	0	0	1	0	1	1	0	1	1	1	0

Figure 6a: Load CR3 for odd channels enabled, MUX disabled, Vfb set to '30' on DAC



Address Register contents =

R/W	R1	R0	A6	A5	A4	A3	A2	A1	A0
0	1	1	1	0	0	0	0	0	0

CR3 Register contents =

D 16	D 15	D 14	D 13	D 12	D 11	D 10	D 9	D 8	D 7	D 6	D 5	D 4	D 3	D 2	D 1	M 5	M 4	M 3	M 2	M 1	F 6	F 5	F 4	F 3	F 2	F 1
1	0	1	0	1	0	1	0	1	0	1	0	1	0	1	0	1	0	0	0	0	0	1	1	1	1	0

Test 6a (contd)



Only odd channel outputs must fire.

Figure 6b: Load CR3 for even channels enabled, MUX disabled, Vfb set to '30' on DAC



Address Register contents =

R/W	R1	R0	A6	A5	A4	A3	A2	A1	A0
0	1	1	1	0	0	0	0	0	0

CR3 Register contents =

D 16	D 15	D 14	D 13	D 12	D 11	D 10	D 9	D 8	D 7	D 6	D 5	D 4	D 3	D 2	D 1	M 5	M 4	M 3	M 2	M 1	F 6	F 5	F 4	F 3	F 2	F 1
0	1	0	1	0	1	0	1	0	1	0	1	0	1	0	1	1	0	0	0	0	0	1	1	1	1	0

Test 6b (contd)



Only even channel outputs must fire.